

MARK IV INTERNET CONNECTION GUIDE

Connection Example


Wireless connection



*Here, "modem" refers to an ADSL modem, optical network unit (ONU), or cable modem.

Instructions

PURCHASE A COMPATIBLE LAN BRIDGE DEVICE



Any LAN bridge compatible with your network should allow you to connect your instrument wirelessly. However, the following devices have been fully tested and are recommended for use with Yamaha instruments:

[LINKSYS WET610N](#)
[BUFFALO WLI-TX4-AG300N](#)


You may need to refer to the manufacturer's instructions to configure your adapter. A full list of compatible adapters is available at the [Yamaha Download Site](#).

CONFIGURE THE BRIDGE ADAPTER



Set up your adapter to connect to your wireless network, following the directions provided for your adapter. If you have any problems connecting the bridge device to your network, please contact the device manufacturer for further support.

ATTACH ETHERNET CABLE To your Disklavier



Attach one end of an Ethernet cable to the rear port of the bridge adapter and the other end to the Ethernet port on your Disklavier.

PRESS



Press the [Internet] button. Congratulations, you are now connected. You should see the Internet Direct Connection home page.

Still can't connect? Follow these instructions...



If you see a screen saying that you are not successfully connected,

PRESS

Yamaha: Connect to Radio Service For ...



you may need to set up your instrument to connect to your network. To do so, press [Setup], then [Network] on your PRC.

CONFIRM NETWORK SETTINGS



Here you can update your DHCP, DNS, proxy, and manual IP settings. In most cases you will not need to edit these settings.

Unless you are manually assigning DNS or IP locations for your instrument, you can set DHCP to "On" and your network should automatically configure the settings to connect successfully.

If you want to enter your DNS server addresses manually, you can choose "DHCP and DNS".

If you also want to enter your IP address, subnet mask, and gateway server information, select "Manual." Also, if you're using a proxy server you will need to enter its name and port here in order to connect.

Note: If you have any questions about the settings for your network, please contact your internet service provider or refer to the documentation for your router.

PRESS



After entering and confirming your network settings, return to the Internet Direct Connection home page by pressing "Internet" on the PRC's main menu.

Attention:

*Once connected to Internet Direct Connection, you'll be able to enjoy Yamaha's Piano Radio services. Don't have a subscription? [Get one now.](#)

*If you have connected successfully and would like to view Radio Service for Piano playback instructions, [visit Playback Instructions.](#)